

30022S4J VARIABLE SPEED CONSTANTS

LOW VOLTAGE

GPD333 CONSTANT	GPD333 VALUE	GPD333 CONSTANT	GPD333 VALUE
00	03	12	040.0
01	0001	13	10.3
02	110	14	10.3
03	220.0	15	22
04	060.0	18	0001
05	001.5	20	1000
06	020.0	43	2
07	001.5	50	60
08	012.0	51	80
09	30	52	110
10	35	53	60
11	080.0		

MOTOR WIRING

Voltage Connection

200 – A (200
240 volts)

380 – C (400
480 volts)

Note: For software date code 8003, you can modify inverter to be used as a "J" or "W".

For "J", go to constant 00 and enter 05, go to constant 66 and enter 01, go to constant 00 and enter 08, then reprogram.

For "W", go to constant 00 and enter 05, go to constant 66 and enter 00, go to constant 00 and enter 08, then reprogram.