

| 3626V5Z MILTOUCH (HIGH VOLTAGE) 5 HP 6 POLE MOTOR ONLY V1000 INVERTER MOTOR 39G809AAT | | | |
|--|----------|----------|--------|
| CONSTANT | VALUE | CONSTANT | VALUE |
| A1-01 | 2 Note 3 | E1-07 | 3 |
| A1-02 | 0 | E1-08 | 22.4 |
| A1-03 | Note 2 | E1-09 | 1.5 |
| B1-01 | 1 | E1-10 | 15 |
| B1-02 | 1 | E2-01 | Note 1 |
| B1-03 | 0 | H1-03 | 7 |
| B1-17 | 1 | H1-04 | 4 |
| C1-01 | 41 | H1-05 | 3 |
| C1-02 | 20 | H1-06 | 5 |
| C1-03 | 140 | H1-07 | A |
| C1-04 | 80 | H2-01 | E |
| C2-01 | 1.0 | L1-01 | 0 |
| C4-01 | .7 | L2-01 | 2 |
| C6-01 | 1 | L3-01 | 0 |
| C6-02 | 2 | L3-04 | 0 |
| E1-01 | 460 | L3-05 | 0 |
| E1-03 | F | L8-05 | 0 |
| E1-04 | 178 | L8-07 | 0 |
| E1-05 | 460 | H1-01 | 40 |
| E1-06 | 60 | H1-02 | 41 |

Note 1: Enter Ampere rating of inverter

Note 2: 2220 is initialize - otherwise 0

Note 3: Set to 0 after programming

Release Date: April 4, 2013

Revision A