

**36026V7J (HIGH VOLTAGE) 300G with Accelerometer
V1000 INVERTER**

| CONSTANT | VALUE | CONSTANT | VALUE |
|----------|----------|----------|-------|
| A1-01 | 2 Note 3 | D1-01 | 11.5 |
| A1-02 | 0 | D1-02 | 130 |
| A1-03 | Note 2 | D1-03 | 8.5 |
| B1-01 | 0 | D1-04 | 160 |
| B1-02 | 1 | D1-05 | 18 |
| B1-03 | 0 | D1-06 | 200 |
| B1-17 | 1 | D1-07 | 63 |
| C1-01 | 35 | D1-08 | 20 |
| C1-02 | 20 | H1-03 | 7 |
| C1-03 | 120 | H1-04 | 4 |
| C1-04 | 80 | H1-05 | 3 |
| C2-01 | 1.0 | H1-06 | 5 |
| C4-01 | .7 | H1-07 | A |
| C6-01 | 1 | H2-01 | E |
| C6-02 | 2 | L1-01 | 0 |
| E1-01 | 460 | L2-01 | 2 |
| E1-03 | F | L3-01 | 0 |
| E1-04 | 200 | L3-04 | 0 |
| E1-05 | 460 | L3-05 | 0 |
| E1-06 | 60 | L8-05 | 0 |
| E1-07 | 3 | L8-07 | 0 |
| E1-08 | 23 | H1-01 | 40 |
| E1-09 | 1.5 | H1-02 | 41 |
| E1-10 | 16 | H2-02 | 16 |
| E2-01 | Note 1 | L4-03 | 167 |
| | | L4-04 | 10 |

Note 1: Enter Ampere rating of inverter

Note 2: 2220 is initialize - otherwise 0

Note 3: Set to 0 after programming

| | | | | |
|------------------------|--------------|---------------|---------------|------|
| Accelerometer setting: | 10 lb weight | min speed 160 | max speed 185 | 3626 |
| | 8 lb weight | min speed 160 | max speed 185 | 3621 |

Release Date: February 24, 2010

Revision B