

**42032X7J (LOW VOLTAGE) – 300G
F7 INVERTER**

CONSTANT	VALUE	CONSTANT	VALUE
A1-00	0	E1-07	3
A1-01	2	E1-08	15/13
A1-02	0	E1-09	1.5
A1-03	Note 2	E1-10	8/7
B1-01	0	E2-01	Note 1
B1-02	1	H1-01	7
B1-03	0	H1-02	4
C1-01	35	H1-03	3
C1-02	20	H1-04	5
C1-03	120	H1-05	A
C1-04	80	H2-01	0
C2-01	1.0	H2-02	16
C6-01	0	H3-05	1F
C6-02	0	L1-01	0
D1-01	11.5	L2-01	2
D1-02	112	L3-01	0
D1-03	10	L3-02	200%
D1-04	164	L3-03	100%
D1-05	17	L3-04	0
D1-06	188	L3-05	0
D1-08	17	L3-06	200
E1-01	240/208	L4-03	160
E1-03	F	L4-04	10
E1-04	188	L8-05	0
E1-05	240/208	L8-07	0
E1-06	60		

Note 1: Enter Ampere rating of inverter

Note 2: 2220 is initialize - otherwise 0

Motor wiring: Wire motor for 208V for 200-208V
Wire motor for 240V for 220-240V

Release Date: April 2, 2014

Revision E