

30022H7J VARIABLE SPEED CONSTANTS

HIGH VOLTAGE

GPD333 CONSTANT	GPD333 VALUE	GPD333 CONSTANT	GPD333 VALUE
00	03	12	040.0
01	0001	13	007.5
02	140	14	006.2
03	400 (346 – 415V) 460 (440 – 480V)	15	13.8
04	060.0	18	0001
05	001.5	20	1000
06	040.0	43	2
07	001.5	50	075.0
08	024.0	51	112.0
09	30	52	140
10	35	53	075.0
11	080.0		

MOTOR WIRING

Voltage	Connection
200 – 240	A (200 volts)
380 – 480	C (400 volts)

Note: For software date code 8003, you can modify inverter to be used as a "J" or "W".

For "J", go to constant 00 and enter 05, go to constant 66 and enter 01, go to constant 00 and enter 08, then reprogram.

For "W", go to constant 00 and enter 05, go to constant 66 and enter 00, go to constant 00 and enter 08, then reprogram.