

42032F7P/W (LOW VOLTAGE) - 300G

GPD506

G5 CONSTANT		G5 VALUE		G5 CONSTANT		G5 VALUE	
NO01		Note 1		NO20		0120.0	
NO02		3 = GPD505 Seq Term - Ref term = GPD506		NO21		0080.0	
NO03		220.00		NO22		.5	
NO04		0 [Ramp to stop]		NO34		0 [No protection]	
NO10		0 [Custom V/F pattern] GPD505 [User Defined V/F pattern] GPD506		NO40		14 [Accel/decel time change]	
NO11		188		NO54		2 = GPD505 5.0 = GPD506	
NO12		220.00		NO55		1 [Continuous operation after power recovery within 2 secs]	
NO13		060.0		NO59		2	
NO14		003.0		NO60		10.0	
NO15		15		NO70		0	
NO16		001.5		NO71		.7	
NO17		8		NO72		0 [Disable]	
NO18		0035.0		NO73		200	
NO19		20		NO74		200	
T-MOTOR WIRING				H-MOTOR WIRING			
Voltage		Connection		Voltage		Connection	
200 – 240		A		200 – 208		240	
				220 – 240		240	

Note 1: Put in 8 to initialize to 2 wire control

Put in 3 to program

Put in 0 to lockout

Note 2: Software version can be viewed under monitor function constant U-10 or on control board.