

42032F7S (LOW VOLTAGE)

GPD505 - 5110/5120 SOFTWARE (Note 2 – Special Edition) / GPD506

G5 CONSTANT	G5 VALUE	G5 CONSTANT	G5 VALUE
NO01	Note 1	NO21	145
NO02	3 = GPD505 Seq term – Ref term = GPD506	NO34	0 [No protection]
NO03	220.00	NO40	14 [Accel/decel time change]
NO04	0 [Ramp to Stop]	NO54	2 = GPD505 5.0 = GPD506
NO10	0 [Custom V/F pattern] GPD505 [User Defined V/F pattern] GPD506	NO55	1 [Continuous operation after power recovery within 2 secs]
NO11	178	NO59	2
NO12	220.00	NO60	10.0
NO13	060.0	NO68	100
NO14	003.0	NO69	.3
NO15	13	NO71	.7
NO16	001.5	NO72	0 [Disable]
NO17	8	NO73	200
NO18	0035.0	NO74	200
NO19	20	NO83	50
NO20	0120.0		

T-MOTOR WIRING		H-MOTOR WIRING	
Voltage	Connection	Voltage	Connection
200 – 240	A	200 – 208	208
380 – 480	C	220 – 240	240

Note 1: Put in 8 to initialize to 2 wire control

Put in 3 to program

Put in 0 to lockout

Note 2: Software version can be viewed under monitor function constant U-10 or on control board.