

**42026/42032 X7W (HIGH VOLTAGE)
V1000 INVERTER**

CONSTANT	VALUE	CONSTANT	VALUE
A1-00	0	E1-08	30
A1-01	2	E1-09	1.5
A1-02	0	E1-10	16
A1-03	Note 2	E2-01	Note 1
B1-01	1	H1-01	40
B1-02	1	H1-02	41
B1-03	0	H1-06	7
B1-17	1	H2-01	E
C1-01	35	H3-13	.5
C1-02	20	L1-01	0
C1-03	120	L2-01	2
C1-04	80	L3-01	0
C2-01	1.0	L3-04	0
C6-01	0	L3-05	0
C6-02	2	L8-05	0
E1-01	460	L8-07	0
E1-03	F		
E1-04	188		
E1-05	460		
E1-06	60		
E1-07	3		

Note 1: Enter Ampere rating of inverter

Note 2: 2220 is initialize - otherwise 0

Motor wiring: Wire motor for 460V for 380-480V

Release Date: August 16, 2010 Revision C