

G3 WELDED CBW 346-480V (HIGH VOLTAGE)**BALDOR INVERTER****LEVEL 1 BLOCKS****Preset Speeds**

Preset speed 1

45 (Note 1)

Accel/Decel Rate

Accel time 1

1.5

Decel time 1

1.0

Input

Operating mode

15 SPD 2 wire

V/Hz and Boost

v/hz profile

3 PT profile

v/hz 3 pt volts %

6.0

v/hz 3 pt frequency

3.0

LEVEL 2 BLOCKS**Output Limits**

min output frequency

1.5

max output frequency

60

Miscellaneous

restart auto/man

Auto

restart fault/hr

10

restart delay

2.0

Brake Adjust

Resistor ohms

Note 2

Watts

Note 3

Note: 1. Must be adjusted to match designed RPM for machine

2. 34 Amp = 25, 55 Amp = 11, 65 Amp = 16.5

3. 34 Amp = 1000, 55 Amp = 4000, 65 Amp = 6000