

**M9V4840C EXTRACTOR (LOW VOLTAGE) FAST ACCELERATION 480G
F7 INVERTER**

CONSTANT	VALUE	CONSTANT	VALUE
A1-00	0	E1-09	1.5
A1-01	2	E1-10	10
A1-02	0	E2-01	NOTE 1
A1-03	2220	H1-01	3
B1-01	0	H1-02	4
B1-02	1	H1-03	5
B1-03	0	H1-04	22
C1-01	60	H1-05	A
C1-02	30	H1-06	F
C1-04	30	H2-01	E
C6-01	0	H2-02	16
C6-02	1	H3-05	1F
D1-01	6	L1-01	0
D1-02	10.3	L2-01	2
D1-03	72	L3-01	1
D1-04	103	L3-02	120
D1-05	140	L3-03	100
D1-06	157	L3-04	0
D1-17	4	L3-05	0
E1-01	240	L3-06	200
E1-03	F	L4-03	130
E1-04	157	L4-04	10
E1-05	240	L8-05	0
E1-06	60	L8-07	0
E1-07	3		
E1-08	15		

NOTE 1: Enter Ampere rating of inverter